

# Product datasheet

Specifications



## front bottom connection kit - for Masterpact NW2000..3200 - 3 poles - fixed

47942

### Main

Range Of Product	MasterPact NW
Product Or Component Type	Front connection
Accessory / Separate Part Category	Connection accessory
Range Compatibility	Masterpact MasterPact NW20 Masterpact MasterPact NW25 Masterpact MasterPact NW32
Poles Description	3P
Mounting Mode	Drawout
[In] Rated Current	2000...3200 A

### Complementary

Location Of Connection	Front
Localisation On Device	Bottom
Connection Pitch	115 mm
Quantity Per Set	3
Accessory / Separate Part Category	Spare part

### Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	12.5 cm
Package 1 Width	12.5 cm
Package 1 Length	37.5 cm
Package 1 Weight	6.264 kg
Unit Type Of Package 2	S03
Number Of Units In Package 2	2
Package 2 Height	30.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	13.015 kg

### Contractual warranty

Warranty	18 months
----------	-----------

Excluding VAT, FCA Jabal Ali & are subject to change – check with your local distributor.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

# Sustainability

**Green Premium™ label** is Schneider Electric’s commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product’s sustainability >](#)

Eu Rohs Directive	Not applicable, out of EU RoHS legal scope
China Rohs Regulation	<a href="#">China RoHS declaration</a> Product out of China RoHS scope. Substance declaration for your information
Circularity Profile	No need of specific recycling operations